



VPO
Visual Persistence Oscilloscope

GDS-2000A Series

FEATURES

- 300/200/100/70MHz Bandwidth, 2 or 4 Input Channels
- 2GSa/s Maximum Real-Time Sampling Rate and 100GSa/s Equivalent Time Sampling Rate
- 2Mpoints Maximum Record length
- VPO Technology to Display Less-Frequently-Occurred Signals
- Fastest Update Rate of 80,000 Waveform Per Second
- Segmented Memory Acquisition and Waveform Search Function
- Optional 8 or 16 Additional Digital Channels with Logic Analyzer (MSO) & Serial Bus I²C/SPI/UART Trigger and Decode Software
- Upgradable DVM and H-Expansion Functionality
- Optional Function Generator
- Flexible Remote Control Connectivity (Standard : USB ; Optional : LAN/ GPIB)

The GDS-2000A Series DSO comes along with a high-value design framework, including 2G Sa/s sampling rate, 2M points record length, 2 or 4 input channels and a large screen color LCD display, to perform very fast waveform acquisition and procession at 80,000 wfms/s update rate utilizing VPO (Visual Persistence Oscilloscope) technology.

The GDS-2000A Series, carrying bandwidths of 300MHz, 200MHz, 100MHz and 70MHz and inputs of 2 and 4 channels, makes up a family of 8 in the whole series. The 2M points record length not only enables the long time waveform storage but also plays the role as a huge database of the input signals for the post-storage waveform analysis. Two powerful functions, Waveform Search and Segmented Memory are available of the GDS-2000A Series to facilitate the search the event of interest from the long record length. Waveform search defines the waveform types for the search whereas segmented memory divides the whole record length into a number of segments. Therefore, the process of searching particular waveforms can be easier and faster.

The ping-pong waveform acquisition design and the advanced VPO-technology-based waveform procession system, greatly enhance the speed and the quality of waveform display of GDS-2000A Series at a very fast update rate of 80,000 waveforms per second.

The optional logic analyzer function allows the signal acquisition through logic triggering and enables the logic waveforms and the analog waveforms to be shown on the same screen for comparison and time correlation analysis. This Mixed Signal Oscilloscope (MSO) function is field-installable with a plug-in module, containing either 8 or 16 input channels, at the rear panel. The MSO function supports the I²C / SPI / UART serial bus trigger and decoding.

The GDS-2000A Series is equipped with all the features that a high-tech DSO should have today. The RS-232C interface, USB ports, and Go-NoGo output are provided as standard, and the Ethernet port, SVGA Video output and GPIB port are available as options for user's free selection. At a moderate cost, GDS-2000A Series is a DSO to provide high customer-value with innovative design.



Front



Rear Panel

APPLICATIONS

- Industrial and Educational R&D Labs
- Product Testing and Quality Assurance
- Embedded System and Mix Signal Design
- System Integration & Debugging
- Maintenance & Repair Service

SPECIFICATIONS

| | | GDS-2072A | GDS-2074A | GDS-2102A | GDS-2104A | GDS-2202A | GDS-2204A | GDS-2302A | GDS-2304A |
|-----------------------------------|--|---|-----------|-----------------------------------|-----------|---|-----------|--|-----------|
| VERTICAL | Channels | 2Ch+EXT | 4Ch+EXT | 2Ch+EXT | 4Ch+EXT | 2Ch+EXT | 4Ch+EXT | 2Ch+EXT | 4Ch+EXT |
| | Bandwidth Rise Time Bandwidth Limit | DC-70MHz(-3dB) 5ns 20MHz | | DC-100MHz(-3dB) 3.5ns 20MHz | | DC-200MHz(-3dB) 1.75ns 20M/100MHz | | DC-300MHz(-3dB) 1.17ns 20M/100M/200MHz | |
| | Vertical Resolution Input Coupling Input Impedance DC Gain Accuracy(**) | 8 bits@1M : 1mV*-10V (*: When the vertical scale is set to 1mV/div, the bandwidth limit will be set to 20MHz automatically) AC, DC, GND 1MΩ // 16pF approx. ±(3% X Readout + 0.1div + 1mV) when 2mV/div or greater is selected ; ±(5% X Readout + 0.1div + 1mV) when 1mV/div is selected (*: The measurement type is average of ≥16 waveforms with vertical position at zero) | | | | | | | |
| | Polarity Maximum Input Voltage Offset Position Range Waveform Signal Process | Normal, Invert 300V (DC+AC Peak), CAT I 1mV/div - 20mV/div : ±0.5V ; 50mV/div - 200mV/div : ±5V ; 500mV/div - 2V/div : ±25V ; 5V/div - 10V/div : ±250V +, -, x, ÷, FFT, FFTrms, d/dt, ∫ dt, √ FFT: Spectral magnitude, Set FFT Vertical Scale to Linear RMS or dBV RMS, and FFT Window to Rectangular, Hamming, Hanning, or Blackman-Harris | | | | | | | |
| TRIGGER | Source Trigger Mode Trigger Type | Ch1, CH2, CH3*, CH4*, Line, EXT, D0-D15** (*: four channel models only. **: Logic analyzer option only) Auto (Supports Roll Mode for 100 ms/div and slower), Normal, Single Edge, Pulse Width, Video, Pulse Runt, Rise & Fall, Alternate, Time out, Event-Delay(1-65,535 events), Time-Delay(10ns-10s), Logic*, Bus* (*with DS2-08LA or DS2-16LA option) 10ns - 10s | | | | | | | |
| | Trigger Holdoff Range Coupling Sensitivity | AC, DC, LF rej., HF rej., Noise rej. DC - 100MHz Approx. 1div or 1.0mV ; 100MHz - 200MHz Approx. 1.5div or 15mV ; 200MHz - 300MHz Approx. 2div or 20mV | | | | | | | |
| EXT TRIGGER | Range Sensitivity | ±15V DC - 100MHz Approx. 100mV 100MHz - 200MHz Approx. 150mV ; 200MHz - 300MHz Approx. 150mV | | | | | | | |
| | Input Impedance | 1MΩ ±3%, -16pF | | | | | | | |
| HORIZONTAL | Time Base Range Pre-trigger Post-trigger Accuracy Real Time Sample Rate ET Sample Rate Record Length Acquisition Mode Peak Detection Average | 1ns/div - 100s/div (1-2.5 increments); ROLL : 100ms/div - 100s/div 10 div maximum 1,000 div max (depend on time base) ±20 ppm over any ≥ 1 ms time interval Max. : 2GSa/s 100GSa/s maximum for all models Max. : 2Mpts Normal, Average, Peak Detect, Single 2ns (typical) Selectable from 2 to 256 | | | | | | | |
| X-Y MODE | X-Axis Input Y-Axis Input Phase Shift | Channel 1 : Channel 3* (*: four channel models only) Channel 2 : Channel 4* (*: four channel models only) ±3° at 100kHz | | | | | | | |
| Cursors AND MEASUREMENT | Cursors Automatic Measurement | Amplitude, Time, Gating Available; Unit : Seconds(S), Hz(1/S), Phase (Degrees), Ratio(%) 36 sets: Pk-Pk, Max, Min, Amplitude, High, Low, Mean, Cycle Mean, RMS, Cycle RMS, Area, Cycle Area, ROVShoot, RPREShoot, FPREShoot, Frequency, Period, RiseTime, FallTime, +Width, -Width, Duty Cycle, +Pulses, -Pulses, +Edges, -Edges, FRR, FRF, FFR, FFF, LRR, LRF, LFR, LFF, Phase | | | | | | | |
| | Control Panel Function Auto Counter Autoset Save Setup Save Waveform | Cursors measurement 6 digits, range from 2Hz minimum to the rated bandwidth Single-button, automatic setup of all channels for vertical, horizontal and trigger systems, with undo Autoset 20set 24set | | | | | | | |
| DISPLAY SYSTEM | TFT LCD Type Display Resolution Interpolation Waveform Display Waveform Update Rate Display Graticule | 8" TFT LCD SVGA color display(LED Back-light) 800 horizontal x 600 vertical pixels (SVGA) Sin(x)/x & Equivalent time sampling Dots, Vectors, Variable persistence(16ms-10s), Infinite persistence 80,000 waveforms per second, maximum 8 x 10 divisions | | | | | | | |
| INTERFACE | RS-232C USB Port Ethernet Port SVGA Video Port GPIB Go/NoGo BNC Kensington Style Lock | DB-9 male connector USB 2.0 Full-speed host port, USB 2.0 Full-speed device port RJ-45 connector, 10/100Mbps with HP Auto-MDIX (option) SVGA output (option) GPIB module (option) 5V Max/10mA TTL open collector output Rear-panel security slot connects to standard Kensington-style lock | | | | | | | |
| LOGIC ANALYZER (OPTION) | Sample Rate Bandwidth Record Length Input Channels Trigger Type Thresholds Threshold Selections Threshold Accuracy User-defined Threshold Range Maximum Input Voltage Minimum Voltage Swing Input Impedance Vertical Resolution | 500MSa/s- 200MHz 2M max 16 Digital (D15 - D0) or 8 Digital (D7-D0) Edge, Pattern, Pulse Width, Serial bus (I ² C, SPI, UART), Parallel Quad-D0 - D3, D4 - D7, ... Thresholds D8-D11*, D12-D15* (*: DS2-16LA only) TTL, CMOS, ECL, PECL, User Defined ±100mV ±10V ±40V ±500mV 101KΩ probe loading 8 pF 1 bit | | | | | | | |
| POWER SOURCE MISCELLANEOUS | Line Voltage Range Multi-Language Menu On-Line Help Time clock | AC 100V ~ 240V, 48Hz ~ 63Hz, auto selection Available Available Time and date, provide the date/time for saved data | | | | | | | |
| DIMENSIONS & WEIGHT | 380(W) X 220(H) X 145(D)mm, Approx. 4.2 kg | | | | | | | | |

Note : Three-year warranty, excluding probes & LCD display panel.

Specifications subject to change without notice.

DS-2000AGD2DH

ORDERING INFORMATION

| | |
|------------------|---|
| GDS-2304A | 300MHz, 4-Channel, Digital Storage Oscilloscope |
| GDS-2302A | 300MHz, 2-Channel, Digital Storage Oscilloscope |
| GDS-2204A | 200MHz, 4-Channel, Digital Storage Oscilloscope |
| GDS-2202A | 200MHz, 2-Channel, Digital Storage Oscilloscope |
| GDS-2104A | 100MHz, 4-Channel, Digital Storage Oscilloscope |
| GDS-2102A | 100MHz, 2-Channel, Digital Storage Oscilloscope |
| GDS-2074A | 70MHz, 4-Channel, Digital Storage Oscilloscope |
| GDS-2072A | 70MHz, 2-Channel, Digital Storage Oscilloscope |

ACCESSORIES

Quick start guide, User manual CD x1, Power cord x1
GTP-070A-4 : 70MHz (10:1/1:1) Switchable passive probe for GDS-2072A/2074A (one per channel)
GTP-150A-2 : 150MHz (10:1/1:1) Switchable passive probe for GDS-2102A/2104A (one per channel)
GTP-250A-2 : 250MHz (10:1/1:1) Switchable passive probe for GDS-2202A/2204A (one per channel)
GTP-350A-2 : 350MHz (10:1/1:1) Switchable passive probe for GDS-2302A/2304A (one per channel)

OPTION

| | |
|-----------------|---|
| DS2-LAN | Ethernet & SVGA output |
| DS2-GPIB | GPIB Interface |
| DS2-FGN | DDS Function Generator |
| DS2-8LA | 8-Channel Logic Analyzer : includes 8-Channel Logic Analyzer Card (GLA-08) and 8-Channel Logic Analyzer Probe (GTL-08LA) |
| DS2-16LA | 16-Channel Logic Analyzer includes 16 Channel Logic Analyzer Card (GLA-16) and 16-Channel Logic Analyzer Probe (GTL-16LA) |

OPTION ACCESSORIES

| | |
|-----------------|---------------------------------|
| GTL-08LA | 8-Channel Logic Analyzer Probe |
| GTL-16LA | 16-Channel Logic Analyzer Probe |
| GLA-08 | 8-Channel Logic Analyzer Card |
| GLA-16 | 16-Channel Logic Analyzer Card |

FREE DOWNLOAD

| | | | |
|-------------|-------------------|--------|-----------------------------|
| PC Software | FreeWave software | Driver | USB driver ; LabView driver |
|-------------|-------------------|--------|-----------------------------|

Global Headquarters

GOOD WILL INSTRUMENT CO., LTD.

No.7-1, Jhongsing Road, Tucheng Dist., New Taipei City 236, Taiwan
T +886-2-2268-0389 F +886-2-2268-0639

China Subsidiary

GOOD WILL INSTRUMENT (SUZHOU) CO., LTD.

No. 521, Zhujiang Road, Snd, Suzhou Jiangsu 215011 China
T +86-512-6661-7177 F +86-512-6661-7277

Malaysia Subsidiary

GOOD WILL INSTRUMENT (M) SDN. BHD.

27, Persiaran Mahsuri 1/1, Sunway Tunas,
11900 Bayan Lepas, Penang, Malaysia
T +604-6309988 F +604-6309989

U.S.A. Subsidiary

INSTEK AMERICA CORP.

3661 Walnut Avenue Chino, CA 91710, U.S.A.
T +1-909-5918358 F +1-909-5912280

Japan Subsidiary

INSTEK JAPAN CORPORATION

2F DSM Shin-Yokohama Bldg, 2-6-3, Shin Yokohama, Kouhoku-ku,
Yokohama, Kanagawa 222-0033 Japan
T +81-45-476-5650 F +81-45-476-5653

Korea Subsidiary

GOOD WILL INSTRUMENT KOREA CO., LTD.

Room No.805, Ace Hightech-City B/D 1Dong,
Mullae-Dong 3Ca 55-20, Yeongduengpo-Gu, Seoul, Korea
T +82-2-3439-2205 F +82-2-3439-2207

GW INSTEK

Simply Reliable

www.gwinstek.com