



VOLTH

VOLTH S-AC100

Non-Contact AC Voltage Detector

100 to 1000V AC detection with flashlight

The **VOLTH S-AC100** The Non-contact AC Voltage Detector was designed for safety purpose and easy to use. Good for all electricians, engineer, services, personnel and general purpose. Just touch the tip to a terminal strip, outlet, or supply cord. When the tip glows red and the unit beeps, you know there's voltage present.

WWW.VOLTH.NET

Features

- Non-Contact Detection of AC Voltage from 50VAC to 1000VAC
- Rugged, double molded case
- Suitable for outlets or against wire insulation testing
- Flashing red LED light indicator
- Built-in bright flashlight with ON/OFF button
- Convenient size with pocket clip
- For use on 50/60Hz circuit
- CAT III 1000 V for protection

Specifications

Standard	CATIV 600V, CAT III 1000V
Operating Range	50 ~ 1000V AC
Operating Temp.	-10°C ~ 50°C
Operating Humidity	0°C ~ 30°C; 95%RH
	30°C ~ 40°C; 75%RH
	40°C ~ 50°C; 45%RH
Size(HxWxD)	158 mm. x 21 mm. x 25 mm.
Weight:	48 g.

(Accuracies are best accuracies for each functions)



Flashing red LED light indicator



LED Lighting

Accessories

2xAAA alkaline battery

(Check the VOLTH website for last updated specifications)

VOLTH Hot Line : +66 8 2337 1333, +66 8 2337 1555 e-mail : info@volth.net

**VOLTH @2014
BANGKOK, THAILAND**

Specifications subject to change without notice.
Assembled & QC in Thailand